

COMS3100/7100 Introduction to Communications
Semester 1, 2011

Tutorial 6

Question 1: Problem 7.1-1 from Carlson

Suppose a commercial AM superhet has been designed such that the image frequency always falls above the broadcast band. Find the minimum value of f_{IF} , the corresponding range of f_{LO} , and the bounds on B_{RF} .

Question 2: Problem 7.1-3 from Carlson

Suppose a commercial AM superhet has $f_{IF} = 455$ kHz and $f_{LO} = 1/2\pi\sqrt{LC}$, where $L=1\mu\text{H}$ and C is a variable capacitor for tuning. Find the range of C when $f_{LO} = f_c + f_{IF}$.

Question 3: Problem 7.1-4 from Carlson

Suppose the RF stage of a commercial AM superhet is a tuned circuit like Fig. 4.1-8 with $L=1\mu\text{H}$ and variable C for tuning. Find the range of C and the corresponding bounds on R .

Question 4: Problem 7.2-1 from Carlson

Four signals, each having $W = 3$ kHz, are to be multiplexed with 1-kHz guard bands between channels. The subcarrier modulation is USSB, except for the lowest channel which is unmodulated, and the carrier modulation is AM. Sketch the spectrum of the baseband and transmitted signal, and calculate the transmission bandwidth.

Question 5: Problem 7.2-2 from Carlson

Do question 4 with AM subcarrier modulation.

Question 6: Problem 7.2-3 from Carlson

Let f_i be an arbitrary carrier in an FDM signal. Use frequency-translation sketches to show that the BPFs in Fig. 7.2-2 are not necessary if the subcarrier modulation is DSB and the detector includes an LPF. Then show that the BPFs are needed, in general for SSB subcarrier modulation.

Question 7: Problem 7.2-4 from Carlson

Ten signals with bandwidth W are to be multiplexed using SSB subcarrier modulation and a guard band B_g between channels. The BPFs at the receiver have $|H(f)| = \exp \{-[1.2(f-f_0)/W]^2\}$ where f_0 equals the center frequency for each subcarrier signal. Find B_g so that the adjacent - channel response satisfies $|H(f)| \leq 0.1$. Then calculate the resulting transmission bandwidth of the FDM signal.

Question 8: Problem 7.2-8 from Carlson

Find the output signals of the quadrature-carrier system in Fig. 7.2-6 when the receiver local oscillator has a phase error Φ' .